

# START BOOSTER P20 12V

TECHNICAL DETAILS . FICHE TECHNIQUE . TECHNISCHE DATEN . CARATTERISTICHE TECNICHE . FICHA TECNICA



					2500
Voltage	Voltage	Tensione di utilizzo	Spannung	Voltaje	12V
Boost rate	Ampères de pointe	Amperaggio di Spunto	Spitzenleistung	Amperaje Arranque	2500 P.LE
Internal battery	Batterie interne	Batteria interna	Kapazität	capacidad de la batería	12V 22 Ah
Cranking rate	Ampérage de démarrage	Amperaggio continuo	Startleistung	Amperaje continuo	850 CA
Recharge	Recharge	Tensione di ricarica	Ladung	Recarga	230V
Charging capacity	Capacité de charge	Alimentazione di carica	Aufladung	Capacidad de carga	12V 1.5 Ah
Charging voltage	Voltage de charge	Voltaggio di carica	Ladungsspannung	Voltaje de carga	max. 14.9V
Life of battery (cycles)	Durée de vie (cycles)	Durata di vita (ciclo)	Lebensdauer (Zyklen)	Duración de vida (Ciclo)	400-500
Number of batteries	Nombre de batteries	Numero di Batteria	Batterien Anzahl	Numero de Bateria	1
Voltage spikes protection	Protecteur de surtension	Protezione sovratensione	Spannungsspitzen geschützt	Protegido contra picos de voltaje	✓
Sealed non-spillable battery	Batterie scellée, étanche	Batteria sigillata	Gasdichter Spezial-Blei-Akku	Bateria estanca	✓
ABS shock-proof cases	Coque en ABS anti-chocs	Scocca in ABS antiurto	ABS Stoßfeste Gehäuseschale	Carcasa de ABS resistente	✓
Automatic charger	Chargeur automatique	Caricatore automatico	Automatisches Netzladegerät	Cargador automatico	✓
Lighter socket cord	Cordon allume cigare	Cavi di ricarica	Zigarrenanzünderkabel	Cable de carga	✓
Completely isolated clamps	Pinces isolées	Pinze isolate	Vollisolierte Zangen	Pinzas aislada	✓
Cable diameter	Diamètre du câble	Diametro di cavi	Kabeldurchmesser	Diametro de cable	25mm <sup>2</sup>
Length of cables	Longueur des câbles	Lunghezza cavi	Kabel Länge	Longitud de cable	87 cm
Dimensions (L x w x h)	Dimensions (L x l x H)	Dimensioni (Lx P x H)	Abmessung (L x B x H)	Dimensiones (LxWxH)	31x10x28
Weight (kg)	Poids (kg)	Peso (kg)	Gewicht (kg)	Peso (kg)	15.4

LEMANIA ENERGY SWITZERLAND

390 Route de Bernex CH- 1233 BERNEX - Tel: Direct+41 22 777 37 05 or +41 22 777 37 03 (3 lines) Fax: +41 22 777 37 04 e-mail: info@lemania-energy.com